

## POWER SMART GR3000/E IN PARALLELO



MODELLO	GR3000/E IN PARALLELO
<b>ALTERNATORE</b>	
<p>Tipo</p> <p>Tensione Nominale/Rated voltage</p> <p>Potenza Nominale/Rated power</p> <p>Potenza Massima/Max Power</p> <p>Capacità serbatoio/Fuel tank capacity</p> <p>Autonomia/Autonomy @75%</p> <p>Avviamento/Start</p> <p>Prese/Sockets</p> <p>Protezione/Protecion</p> <p>Presa DC/DC Output</p> <p>kit Carrello/Trolley kit</p> <p>Rumorosità/Noise Level</p> <p>Dimensioni/Dimensions</p> <p>Peso/Weight</p> <p><b>codice</b></p>	<p><b>GENERATORE AD INVERTER PREDISPOSTO PER IL FUNZIONAMENTO IN PARALLELO CON ALTRA MACCHINA UGUALE (BOX PARALLELO OPTIONAL); INVERTER GENERATOR ARRANGED FOR PARALLEL OPERATION WITH ANOTHER EQUAL MACHINE (PARALLEL BOX OPTIONAL)</b></p> <p>230V</p> <p>2,8kW</p> <p>3,1kW</p> <p>9 litri/litres</p> <p>giri fissi/fixed rpm                    7,7h</p> <p>giri variabili/variable rpm        8,7h</p> <p>AUTOAVVOLGENTE/RECOIL mod. GR3000iN</p> <p>AVVIAMENTO ELETTRICO/ELECTRICSTART mod. GR3000EiN (Batteria 6,5A inclusa/6,5A battery included)</p> <p>2 x schuko 16A</p> <p>basso livello olio/low oil level</p> <p>inclusa/included</p> <p>incluso/included</p> <p>68 dBA@7m</p> <p>498x290x459 mm</p> <p>37 kg (iN) - 40 kg (iNE)</p> <p><b>35456</b>                    GR3000iN PARALLELO</p> <p><b>37926</b>                    GR3000EiN PARALLELO</p>